Scrubs/ Uniform Wash Bag

Many NHS staff and other key workers are being advised to remove their uniforms before they go home. Others are changing more frequently at work and need to wash multiple sets of scrubs or other uniform pieces. These bags are designed to hold the

dirty uniform, and or shoes so that the whole thing can be stuffed/ emptied into the washing machine and then cleaned thoroughly on a hot wash. The exact size of these bags isn't vital. About 18-20" square is great, so you can make one from a half metre of 42" wide fabric, or a couple of fat quarters. A pillowcase can also be used or you could cut up Duvet covers etc. The most important thing is that the fabric and any ties or cords will stand a hot 60 degree

wash. 100% cotton or most cotton mixes will be fine.

These will be washed frequently so they need to be very sturdy. If you have an over locker, you can over lock the seams, but if not the instructions below show you how to do any seams with a French seam technique.

You need to make a channel at the top of the bag for the draw cords. You can turn the top

edge and make a channel, but you need to be able to get the cord in, so working some buttonholes will allow you to do that neatly. Another option is to apply a channel on the outside using 1" wide twill tape or bias binding. I'll show you how later in the handout. An applied channel works great if you are repurposing a pillowcase.

Basic Requirements (all fabrics and cords should be hot washable.)

- Approximately $\frac{1}{2}$ m of fabric. This could be-
 - 2 fat quarters
 - A pillowcase
 - A piece of fabric about 20" x 40"
- 2m of draw cord

INSTRUCTIONS (20" x 40" Fabric - French seams)











3. This shows the folds that will make	4. Fold up the channel and on the
the channel for your cords. Don't sew	right side, mark the position of the
the channel just yet. You need the	button holes. They are indicated in red
folds so you can tell where to put the	above. The bit at the top is the folded
button holes.	over other end so you can see the
	relative positions of the two button holes.


5. This is the close up notice how the	6. Get your sewing machine book out
buttonhole is going to lay on the	and work a buttonhole according to the
outside but on the channel.	instructions do a test first so you know which way it will start sewing!
	Carefully cut the hole.
7. FRENCH SEAM - fold up the bag	8. Turn the bag wrong sides out and
piece right sides OUT and sew a	press the seams so the seam is on the
narrow 9 less than $\frac{1}{4}$ " seam down both	edge of the bag. The stitch down the
sides. Trim any threads.	sides $\frac{3}{8}$ " encasing all the raw edges.

©Rebecca Preen 2020 www.fblquiltingandcrafts.co.uk Page 2 of 3 Version 1 -(07-Apr-20) Uniform Drawstring bag - Instructions This pattern is provided freely for non commercial use for the purposes of facilitating local production of bags for charitable purposes

9. Fold the French seam to the side	10. Turn the pressed section down to
and topstitch it down just the top	make the channel and stitch close to
couple of inches.	the bottom folded edge all the way around the top.
11. Cut a piece of twill tape twice the length of the top of the bag, plus a few inches for the knot. Use a safety pin and thread the tape through the channel all the way around and back out the same hole. Tie the two ends into a knot.	12. To make the draw cord, you the thread a second cord into the second hole and all the way around and back up the second hole. Tie a knot. Now when you pull the two ends, one pulls against the other closing the bag.

For using an overlocker....

Instead of steps 7-9 fold the fabric right sides TOGETHER and over lock. Then proceed with steps 10 onwards.



If you are using a pillowcase or want to make the channel with Bias or other tape ont he outside, Cut 2 pieces of 1" bias tape that are 1" shorter than the edge of your bag. Turn a $\frac{1}{4}$ " on the short edges and stitch (red line). Then position the tape centrally on each side and stitch down the long edges (green lines). Insert the cords as before.